

Matrox Solios eCL/XCL

Camera Interface Application Note

UNIQ UP-1800DS-CL

January 5, 2007

Basics about the
camera

Camera Descriptions

- Effective resolution: $1380 \times 1037 \times 10\text{-bit}$ @ 30 fps.
- Camera Link BASE interface (single tap).
- Progressive scan.
- External or internal sync.
- External or internal exposure control.
- 50 MHz pixel clock rate.


Interface Mode

- Continuous
- Asynchronous reset (pulse width control)

Camera Interface Briefs

Mode 1: Continuous

- $1380 \times 1037 \times 10\text{-bit}$ @ 30 fps.
- Camera Link BASE interface (single tap).
- Progressive scan.
- Matrox Solios eCL/XCL receiving LDV, FDV, CLK and video from camera.
- DCF used: [UP1800DSCL1380x1037Con.DCF](#)



Mode 2: Asynchronous reset

- $1380 \times 1037 \times 10\text{-bit}$.
- Camera Link BASE interface (single tap).
- Progressive scan.
- Matrox Solios eCL/XCL receiving external trigger signal.
- Matrox Solios eCL/XCL sending VINT (CC1) signal to camera to initiate the exposure.
- Matrox Solios eCL/XCL receiving LDV, FDV, CLK and video from camera.

Mode of operations as
per Matrox Imaging (in
parentheses as per
camera manufacturer)

Basics about the
interface modes

Matrox Solios eCL/XCL

Camera Interface Application Note

UNIQ UP-1800DS-CL


January 5, 2007

Basics about the
interface modes

Camera Interface Briefs (cont.)

Mode 2: Asynchronous reset

- DCF used: [UP1800DSCL1380x1037Async.DCF](#)



Specifics about the
interface modes

Camera Interface Details

Mode 1: Continuous

- **Frame Rate:** Matrox Solios eCL/XCL receives the continuous video from the camera at 30 frames per second (full resolution).
- **Exposure time:** Exposure time is determined by the camera shutter setting. Refer to the camera manual for more information.
- **Camera switch settings:** Refer to the camera manual.

Mode 2: Asynchronous Reset

- **Frame rate:** The frame rate is determined by the frequency of the external trigger signal.
- **Exposure time:** The width (falling edge to rising edge) of the VINT (CC1) signal is the exposure time. The exposure time can be modified in the DCF using Matrox Intellicam or with the MIL MdigControl() function. Consult the respective manual for more information.
- **Camera Control:** The camera mode is set using the camera's switches. Refer to the camera manual (or contact the manufacturer) for more information.

Matrox Solios eCL/XCL

Camera Interface Application Note

UNIQ UP-1800DS-CL

January 5, 2007

Cabling details for the
interface modes

Cabling Requirements

Mode 1: Continuous

- **Cable and Connection:** Standard Camera Link cable.

Mode 2: Asynchronous reset

- **Cable and Connection:** Standard Camera Link.
- **External trigger:** External trigger should be connected to the OPTO TRIG input of the 9-pin connector (pins 7 and 2) on the Expanded I/O adapter bracket.

EXPANDED I/O BRACKET

(9-pin connector)

		External Trigger Source	
OPTOTRIG +	07	←	SIGNAL --
OPTOTRIG -	02	←	GROUND --

The DCFs mentioned in this application note are also attached (embedded) to this PDF file – use the Adobe Reader's View File Attachment to access the DCF files. The information furnished by Matrox Electronics System, Ltd. is believed to be accurate and reliable. Please verify all interface connections with camera documentation or manual. Contact your local sales representative or Matrox Sales office or Matrox Imaging Applications at 514-822-6061 for assistance. © Matrox Electronic Systems Ltd, 2007-2011.

Matrox Electronic Systems Ltd.

1055 St. Regis Blvd.
Dorval, Quebec H9P 2T4
Canada
Tel: (514) 685-2630
Fax: (514) 822-6273
SOL-CID-050

