

Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030

August 8, 2006

Basics about the
camera

Mode of operations as
per Matrox Imaging (in
parentheses as per
camera manufacturer)

Basics about the
interface modes

Camera Descriptions

- Effective resolution: up to 2098 pixels/line @ 10.82k line per second.
- Camera Link MEDIUM interface (10-bit RGB).
- External and internal sync.
- External or internal exposure control.
- 25 MHz pixel clock rate.

Interface Mode


- Fixed line scan rate (External Trigger*)
- Variable line scan rate (External Trigger)
- Fixed line scan rate with frame trigger (External Trigger*)
- Variable line scan rate with frame trigger (External Trigger)
- Fixed line scan rate with variable frame size (External Trigger*)
- Variable line scan rate with variable frame size (External Trigger)

Camera Interface Briefs

*or Free Run mode

Mode 1: Fixed line scan rate

- Up to 2098 pixels/line.
- Camera Link MEDIUM interface (10-bit RGB).
- DCF configured for 1000 lines per virtual frame.
- Matrox Solios eCL/XCL sending periodic EXPOSURE1 (CC1) signal to camera.
- Matrox Solios eCL/XCL receiving HSYNC (LVAL), PIXEL CLOCK (XCLK@ 25 MHz) and video data from camera.
- DCF used: [SUCL2030_2098_RGB10bitFLS.DCF](#)



Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Basics about the
interface modes

Camera Interface Briefs (cont.)


Mode 2: Variable line scan rate

- Up to 2098 pixels/line.
- Camera Link MEDIUM interface (10-bit RGB).
- DCF configured for 1000 lines per virtual frame.
- Matrox Solios eCL/XCL receiving external TTL line trigger signal.
- Matrox Solios eCL/XCL sending EXPOSURE1 (CC1) signal to camera.
- Matrox Solios eCL/XCL receiving HSYNC (LVAL), PIXEL CLOCK (XCLK@ 25 MHz) and video data from camera.
- DCF used: [SUCL2030_2098_RGB10bitVLS.DCF](#)



Mode 3: Fixed line scan rate with frame trigger

- Up to 2098 pixels/line.
- Camera Link MEDIUM interface (10-bit RGB).
- DCF configured for 1000 lines per virtual frame.
- Matrox Solios eCL/XCL receiving external TTL frame (virtual) trigger signal.
- Matrox Solios eCL/XCL sending periodic EXPOSURE1 (CC1) signal to camera.
- Matrox Solios eCL/XCL receiving HSYNC (LVAL), PIXEL CLOCK (XCLK@ 25 MHz) and video data from camera.
- DCF used: [SUCL2030_2098_RGB10bitFLSFT.DCF](#)



Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Basics about the
interface modes

Camera Interface Briefs (cont.)


Mode 4: Variable line scan rate with frame trigger

- Up to 2098 pixels/line.
- Camera Link MEDIUM interface (10-bit RGB).
- DCF configured for 1000 lines per virtual frame.
- Matrox Solios eCL/XCL receiving external TTL frame (virtual) and line trigger signals.
- Matrox Solios eCL/XCL sending EXPOSURE1 (CC1) signal to camera.
- Matrox Solios eCL/XCL receiving HSYNC (LVAL), PIXEL CLOCK (XCLK@ 25 MHz) and video data from camera.
- DCF used: [SUCL2030_2098_RGB10bitVLSFT.DCF](#)



Mode 5: Fixed line scan rate with variable frame size

- Up to 2098 pixels/line.
- Camera Link MEDIUM interface (10-bit RGB).
- DCF configured for 1000 lines per virtual frame.
- Matrox Solios eCL/XCL receiving external TTL frame (virtual) trigger signal.
- Matrox Solios eCL/XCL sending periodic EXPOSURE1 (CC1) signal to camera.
- Matrox Solios eCL/XCL receiving HSYNC (LVAL), PIXEL CLOCK (XCLK@ 25 MHz) and video data from camera.
- DCF used: [SUCL2030_2098_RGB10bitFLSVF.DCF](#)



Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Basics about the
interface modes

Camera Interface Briefs (cont.)

Mode 6: Variable line scan rate with variable frame size

- Up to 2098 pixels/line.
- Camera Link MEDIUM interface (10-bit RGB).
- DCF configured for 1000 lines per virtual frame.
- Matrox Solios eCL/XCL receiving external TTL frame (virtual) and line trigger signals.
- Matrox Solios eCL/XCL sending EXPOSURE1 (CC1) signal to camera.
- Matrox Solios eCL/XCL receiving HSYNC (LVAL), PIXEL CLOCK (XCLK@ 25 MHz) and video data from camera.
- DCF used: [SUCL2030_2098_RGB10bitVLSVF.DCF](#)



Specifics about the
interface modes

Camera Interface Details

Mode 1: Fixed line scan rate

- **Line rate:** The frequency of the periodic EXPOSURE1 (CC1) signal determines the camera's line rate. The EXPOSURE1 (CC1) signal period is set in the DCF to **128 μ s** which translates into a **7.81 kHz** line rate. The maximum line rate for this camera equals **10.82 kHz**.
- **Exposure time:** For **External Trigger mode** the exposure time is period between the rising edges of the EXPOSURE1 (CC1) signal. The default exposure time for this DCF equals **40 μ s**. Maximum/minimum exposure time per line for this DCF is **671 ms** and **40 ns** respectively. The exposure time can be modified in the DCF using Matrox Intellicam or with the MIL MdigControl() function. Consult the respective manual for more information.
- **Camera communication:** This DCF will also work with the **Free Run mode**, however External Trigger mode is recommended. Set the mode (as shown in table below) via the NED Camera Link communication tool (NED Ctrl). Refer to the camera manual for additional information.

Controller Item	Command	Value	Description
Drive clock	x	0	Internal clock
Exposure mode	t	0 or 2	Free Run or External Trigger mode

Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Specifics about the
interface modes

Camera Interface Details (cont.)

Mode 1: Fixed line scan rate

- Timing diagram:



Mode 2: Variable line scan rate

- **Line rate:** The line rate is controlled by the frequency of the external TTL line trigger signal. The line trigger signal period must be larger than the total duration of the exposure time (low level duration of the timer), the internal delay of the camera ($\approx 2.5 \mu\text{s}$) and the line readout ($83.92 \mu\text{s}$). The Exposure1 (CC1) signal is sent periodically to the camera to generate a constant exposure time (see below). However in this DCF, the Matrox Solios eCL/XCL grabs the next valid LVAL from the camera following the rising edge of the External Line Trigger signal.
- **Exposure time:** Refer to Mode 1: Fixed line scan rate.
- **Camera communication:** Set the mode (as shown in table below) via the NED Camera Link communication tool (NED Ctrl). Refer to the camera manual for additional information.

Controller Item	Command	Value	Description
Drive clock	x	0	Internal clock
Exposure mode	t	2	External Trigger mode

Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Specifics about the
interface modes

Camera Interface Details (cont.)


Mode 2: Variable line scan rate

- Timing diagram:



Mode 3: Fixed line scan rate with frame trigger

- **Line/frame rate:** The line rate is fixed and controlled by the period of EXPOSURE1 (CC1) signal. The virtual frame rate is variable and controlled by the period of the external frame trigger signal, however the external trigger period must always be greater than the total time of the number of lines captured. The number of lines per virtual frame (maximum of 1000 for this DCF) is fixed and controlled by the vertical timing of the DCF. Capture of the lines will start with the rising edge of the frame trigger signal.
- **Exposure time:** Refer to Mode 1: Fixed line scan rate.
- **Camera communication:** Refer to Mode 1: Fixed line scan rate.
- Timing diagram:



Matrox Solios eCL/XCL

Camera Interface Application Note


NED SUCL 2030

August 8, 2006

Camera Interface Details (cont.)

Mode 4: Variable line scan rate with frame trigger

- **Line/frame rate:** The line rate is controlled by the frequency of the external TTL line trigger signal. The line trigger signal period must be larger than the total duration of the exposure time duration. The Exposure1 (CC1) signal is sent periodically to the camera to generate a constant exposure time (see below). However in this DCF, the Matrox Solios eCL/XCL grabs the next valid LVAL from the camera following the rising edge of the External Line Trigger signal. The virtual frame rate is variable and controlled by the period of the external frame trigger signal, however the external trigger period must always be greater than the total time of the number of lines captured. The number of lines per virtual frame (maximum of 1000 for this DCF) is fixed and controlled by the vertical timing of the DCF. Capture of the lines will start with the rising edge of the frame trigger signal.
- **Exposure time:** Refer to Mode 2: Variable line scan rate.
- **Camera communication:** Refer to Mode 2: Variable line scan rate.
- **Timing diagram:**



Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Specifics about the
interface modes

Camera Interface Details (cont.)

Mode 5: Fixed line scan rate with variable frame size

- **Line/frame rate:** The line rate is fixed and controlled by the period of EXPOSURE1 (CC1) signal. The number of lines per virtual frame (maximum of 1000 for this DCF) is variable and controlled by the frame trigger signal. Matrox Solios eCL/XCL captures lines during the high level of the frame trigger signal. To modify the maximum amount of lines captured, change the active vertical timing period in the DCF. Capture of the lines will start with the rising edge of the frame trigger signal.
- **Exposure time:** Refer to Mode 1: Fixed line scan rate.
- **Camera communication:** Refer to Mode 1: Fixed line scan rate.
- **Timing diagram:**



Mode 6: Variable line scan rate with variable frame size

- **Line/frame rate:** The line rate is controlled by the frequency of the external TTL line trigger signal. The line trigger signal period must be larger than the total duration of the exposure time duration. The Exposure1 (CC1) signal is sent periodically to the camera to generate a constant exposure time (see below). However in this DCF, the Matrox Solios eCL/XCL grabs the next valid LVAL from the camera following the rising edge of the External Line Trigger signal. The number of lines per virtual frame (maximum of 1000 for this DCF) is variable and controlled by the frame trigger signal. Matrox Solios eCL/XCL captures lines during the high level of the frame trigger signal. To modify the maximum amount of lines captured, change the active vertical timing period in the DCF. Capture of the lines will start with the rising edge of the frame trigger signal.
- **Exposure time:** Refer to Mode 1: Fixed line scan rate.
- **Camera communication:** Refer to Mode 2: Variable line scan rate.

Continued....

Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030


August 8, 2006

Specifics about the
interface modes

Camera Interface Details (cont.)

Mode 6: Variable line scan rate with variable frame size

Timing diagram:



Cabling details for the
interface modes

Cabling Requirements

Mode 1: Fixed line scan rate

- Cable and Connection:** Standard Camera Link cable.

Mode 2: Variable line scan rate

- Cable and Connection:** Standard Camera Link.
- External trigger:** External line trigger should be connected to the OPTO TRIG input of the 9-pin connector (pins 7 and 2) on the External I/O adapter bracket:

EXTERNAL I/O BRACKET (9-pin connector)

Pin Name	Pin no.	External Trigger Source
OPTO_AUX_IN0 +	07	← LINE TRIGGER (TTL FORMAT)
OPTO_AUX_IN0 -	02	← LINE TRIGGER (GROUND)

Mode 3: Fixed line scan rate with frame trigger

- Cable and Connection:** Standard Camera Link.
- External trigger:** External line trigger should be connected to the OPTO TRIG input of the 9-pin connector (pins 4 and 5) on the External I/O adapter bracket:

EXTERNAL I/O BRACKET (9-pin connector)

Pin Name	Pin no.	External Trigger Source
OPTO_AUX_IN1 +	04	← FRAME TRIGGER (TTL FORMAT)
OPTO_AUX_IN1 -	05	← FRAME TRIGGER (GROUND)

Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030

August 8, 2006

Cabling details for the
interface modes

Cabling Requirements

Mode 3: Fixed line scan rate with frame trigger

- **Cable and Connection:** Standard Camera Link.
- **External trigger:** External line trigger should be connected to the OPTO TRIG input of the 9-pin connector (pins 4 and 5) on the External I/O adapter bracket:

EXTERNAL I/O BRACKET

(9-pin connector)

Pin Name	Pin no.		External Trigger Source Pin Name
OPTO_AUX_IN1 +	04	←	FRAME TRIGGER (TTL FORMAT)
OPTO_AUX_IN1 -	05	←	FRAME TRIGGER (GROUND)

Mode 4: Variable line scan rate with frame trigger

- **Cable and Connection:** Standard Camera Link.
- **External trigger:** External frame and line triggers should be connected to the OPTO TRIG inputs of the 9-pin connector on the External I/O adapter bracket:

EXTERNAL I/O BRACKET

(9-pin connector)

Pin name	Pin no.		External Trigger Sources Pin name
OPTO_AUX_IN1 +	04	←	FRAME TRIGGER (TTL FORMAT)
OPTO_AUX_IN1 -	05	←	FRAME TRIGGER (GROUND)
OPTO_AUX_IN0 +	07	←	LINE TRIGGER (TTL FORMAT)
OPTO_AUX_IN0 -	02	←	LINE TRIGGER (GROUND)

Mode 5: Fixed line scan rate with variable frame size

- **Cable and Connection:** Standard Camera Link.
- **External trigger:** External trigger should be connected to the OPTO TRIG input (pins 4 and 5) of the 9-pin connector on the External I/O adapter bracket:

EXTERNAL I/O BRACKET

(9-pin connector)

Pin name	Pin no.		External Trigger Sources Pin name
OPTO_AUX_IN1 +	04	←	FRAME TRIGGER (TTL FORMAT)
OPTO_AUX_IN1 -	05	←	FRAME TRIGGER (GROUND)

Matrox Solios eCL/XCL

Camera Interface Application Note

NED SUCL 2030

August 8, 2006

Cabling Requirements (cont.)

Mode 6: Variable line scan rate with variable frame size

- **Cable and Connection:** Standard Camera Link.
- **External trigger:** External frame and line triggers should be connected to the OPTO TRIG inputs of the 9-pin connector on the External I/O adapter bracket:

EXTERNAL I/O BRACKET

(9-pin connector)

Pin name

Pin no.

External Trigger Sources

Pin name

OPTO_AUX_IN1 +	04	←	FRAME TRIGGER (TTL FORMAT)
OPTO_AUX_IN1 -	05	←	FRAME TRIGGER (GROUND)
OPTO_AUX_IN0 +	07	←	LINE TRIGGER (TTL FORMAT)
OPTO_AUX_IN0 -	02	←	LINE TRIGGER (GROUND)

The DCFs mentioned in this application note are also attached (embedded) to this PDF file – use the Adobe Reader's View File Attachment to access the DCF files. The information furnished by Matrox Electronics System, Ltd. is believed to be accurate and reliable. Please verify all interface connections with camera documentation or manual. Contact your local sales representative or Matrox Sales office or Matrox Imaging Applications at 514-822-6061 for assistance. © Matrox Electronic Systems Ltd, 2006-2011.

Matrox Electronic Systems Ltd.

1055 St. Regis Blvd.
Dorval, Quebec H9P 2T4
Canada
Tel: (514) 685-2630
Fax: (514) 822-6273
SOL-CID-032

