

## Touch Panel Compile Guide

### Simpl Windows:

- Open MVX6100DecoderCrestronModule > MVX6100DecoderCrestronModule.smw  
Go to Project > Configure System > Crestron Devices > Touchpanels > TouchPanels(Ethernet) to choose the touch panel you want, drag and drop it into the red arrow Ethernet Units on the System Views.
- Go to Project > Program System, double click this touch panel under Slot-02 to open it in detail view, press Shift and select the symbols in Xpanel detail view then drag and drop them on the same places in the touch panel detail view.
- Right click the touch panel under Central Control Modules > Slot-02 > Make Symbols Complete.
- Go to Project > Convert/Compile it, then Send the compiled file to the correct processor using the correct connection type (TCP or USB) and the correct processor's IP address.

### VTPro-e:

- Make a copy of the Xpanel file MVX6100DecoderCrestronModuleXpanel.vtp as a new Xpanel file for example newXpanel.vrp and open the new file.
- Right click on this newXpanelName > Save Project As with the correct touch Panel Type as yours and save the project.
- Go to File > Compile Project, choose the TCP connection and choose or enter your touch panel's IP address, click OK and Press send to complete it.